

Standalone

SOYAL[®]

Access control system

SOYAL standalone controller reader optimized for low budget door access control system. Effectively control who can and cannot enter. Simple to use without PC. Highly affordable for small offices below 50 employees while maintaining reliable quality.

AR723_B



AR723_R



Proximity Card Only - AR723H

No need any pin number programming. Card enrollment and delete is done using master card. Just flash mastercard then flash proximity card to enroll. Flash master card longer (8sec) will delete all cards. Super simple usage with good security.

Pin number only - AR721KP

Having problem, forgot to bring the proximity card? 721KP work only by pin number for maximum convenient and optimum security. Just key in the 4 digit security pin to gain access. Programmable different pin up to 250 users.



AR721_KP



no need PC



user friendly



more affordable



modern design

RFID



ONE FOR ALL HARDWARE, ALL IN ONE SOFTWARE




AR723H

Specification

Model No.	AR-723H (B/R)
Frequency	125kHz
Voltage	12VDC
Power Consumption	< 1W
User Capacity	100
Operating Temperature	-20°C to +75°C
Active Distance	6 cm
Indicator	1 Bi-color LED & 1 Buzzer
Weatherproof	NONE
Color	Blue/Red
Dimension (mm)	81(L) x 43(W) x 18(H)
N.W. (g)	40±5
Housing Material	ABS
Relay	Door open relay - 10sec Alarm relay - 10sec

Diagram



Adding Tag

1. Present Master Card
2. After 3 short beeps (Access programming mode)
3. Present one new card at a time
4. Present Master Card (Exit programming mode)

Deleting Tag

1. Present Master Card
2. After 3 short beeps (Access programming mode)
3. 1 long warning beep after 2 secs
4. 5 short beeps after 5 secs: cards cleared.


PS: Once Master Card is presented after one warning beep, all card data will be cleared

AR721KP

Specification

Model No.	AR721KP
Reading	Pin number only
Door relay	12V / 2A N.O. / N.C. / COM Momentary / Latch type Pre-set time 0.1 to 600 sec
Alarm relay	NONE
Serial data port	NONE
Input port	1 for push button
Power consumption	12VDC. Less than 2W
Dimension	112(L) x 76(W) x 25(H)

Diagram



Accessories



SOYAL also have complete Networking Access Control System that supports user friendly software. Software provides more power function to better manage larger scale premises. Contact your nearest dealer for more information on SOYAL intergrated access control management software.

Authorized dealer